

Operating your JET Revelation

How to use the JET Revelation

- Using the Pedal
- Saving Presets

Using the Pedal

Mix Knob

The mix knob controls the overall blend between the wet and dry signal. Fully counterclockwise is 100% dry signal and no reverb will pass to the output jacks. Fully clockwise is 100% wet signal and no dry signal will pass to the output jacks. A 50/50 mix is approximately 10 to 11:00.

Decay Knob

The decay knob effects how long the reverb trails. The range is from 50 milliseconds to over 1 minute.

Cntrl 1 Knob

The control knob function changes depending on the algorithm:

- Cyan Sky Blue Algorithm - Controls the amount of modulation present in the reverb trails. The modulation parameters are fixed. Think of this as a volume level; the more you turn it up, the more present the modulation will be.
- White Ice Algorithm - Controls the amount of upper octave shimmer present in the reverb trails. The decay knob and the control 1 knob are interactive with each other. The decay knob controls how long the shimmer stays in the trails of the reverb; the higher the decay, the longer the shimmer is present in the trails. The control 1 knob acts as a volume control for the level of shimmer in the reverb.
- Yellow Sub Algorithm - Controls the amount of lower octave in the reverb trails. Think of the control 1 knob as a volume knob, controlling the level of lower octave in the reverb trails.

Using the Soft-Click Switches

To engage the reverb, do a short press of the bypass switch. The bypass LED will turn on and all three knobs will be active. You can dial in the sounds any way you like as you are in Live Mode. To switch between Live Mode and Preset Mode, do a short press of the preset switch. The preset LED will turn on and all the knobs will be locked/inactive. To exit Preset Mode, just press the preset

switch again and all knobs will be back to Live Mode.

Our soft click Bypass and Preset switches are smart switches which have several different timed based functions to control various features of the pedal. Since there is a lot of time based *magic* happening behind the scenes, please note that it is possible to rapidly press the switch so fast that it will not recognize the press. A good solid press should be sufficient to engage the Bypass or Preset switch.

Time based functions are as follows:

- To switch algorithms on the fly, press and hold the Bypass switch for at least 3/4's of a second and upon releasing the Bypass switch you will cycle through to the next algorithm.
- To switch presets on the fly, press and release both of the Bypass and Preset switches at the same time. This will cycle through each preset until it reaches the end and then will cycle back to the beginning. You can cycle through your presets in any state that the pedal is in (off, on, or in preset mode). Do not press and hold both switches for longer than 2 seconds as this will enter "Preset Save Mode".
- To engage infinite Bloom, press and continue to hold the Preset switch, as long as the switch is being held down the Preset LED will begin to flash and the Decay knob will gracefully increase until it reaches its maximum setting. Once the Preset switch is released the Preset LED will continue to flash letting you know the Decay knob is gracefully returning to its original setting.
- When switching between modes (Live or Preset) and you are transitioning from a long decay to a shorter decay, the pedal automatically enters into a "graceful transition" state, the Preset LED will begin to flash letting you know that the Decay knob is gracefully returning to its new setting. Please note that whenever the Preset LED is flashing, both Bypass and Preset switches will be inactive until the Decay knob has settled to its new position.

Saving Presets

To enter "Preset Save Mode", press and hold both the Bypass and Preset switch for longer than 2 seconds and upon releasing both switches the Bypass LED will begin to flash confirming you are in "Preset Save Mode".

Once in "Preset Save Mode" a short press of the Preset switch will change the preset location (Mix LED will change colors) and a short press of the Bypass switch will change the algorithm (Decay LED will change colors). Call up your desired algorithm, preset location, and dial in the positions of each knob. Press and hold the Preset switch for at least 2 seconds to save that preset and stay in "Preset Save Mode". If you wish to save the current preset and exit "Preset Save Mode", hold down both the Preset switch and Bypass switch for at least 2 seconds. Upon releasing the Bypass LED will stop flashing confirming you've exited "Preset Save Mode".

To exit "Preset Save Mode" without saving over any previously stored presets, press and hold the Bypass switch for longer than 2 seconds and upon releasing the Bypass switch you will exit the "Preset Save Mode"