

Description

The U6 Trio is a triple switch expander for the Unity6 midi controller/loop switcher. Each switch has two press actions (short press & long press) and each press action can be programmed to control any feature within the Unity6.

Daisy chain up to 2 Trio's together (per UniPort) to add up to 12 additional switches for the ultimate control over your Unity6.

Each switch and press action can be programmed globally (same feature is accessible across all banks) or each bank can have global overrides programmed to each switch/press action which can be used to fire presets/midi messages within each bank.

Example Use Cases:

- **Global Programming** (works across all Unity6 banks)
 - Short press A, B, C toggle Loops 1, 2, 3 on/off
 - Long press A, B, C toggle Loops 4, 5, 6 on/off
 - Short press A, B, C toggle Loops 1, 2, 3 on/off
 - Long press A bank down
 - Long press B toggle boost on/off
 - Long press C bank up
 - Short press A decrease BPM, short press B toggle amp channel, short press C increase BPM
 - Long press A bank down
 - Long press B toggle Red Remote
 - Long press C bank up
 - **Global Override Programming** (works only in a specific Unity6 bank)
 - Short press A fire any message (or group of messages) assigned to Preset 2 (Switch 2)
 - Short press B fire any message (or group of messages) assigned to Preset 5 (BPM knob)
 - Short press C fire any message (or group of messages) assigned to Preset 1 (Switch 1)
 - (Don't override Global messages programmed to Long Presses)
 - Long Press A bank down
 - Long press B toggle boost
 - Long press C bank up
-

Revision #3

Created 29 July 2025 20:46:59 by Junior Thomason

Updated 5 August 2025 21:10:23 by Junior Thomason