

FAQ

Frequently asked questions

- [Can I Control "Insert Pedal Name Here" w/ the Unity6?](#)
- [Will the Unity6 Allow Me to Have Snapshots for my Pedalboard?](#)
- [Are the 6 Loops Mono or Stereo?](#)
- [Can I Add a 2-Button Aux Switch to the Unity6?](#)
- [Is There a Set List Feature in the Unity6?](#)
- [Is There a Factory Reset for the Unity6?](#)
- [My Unity6 Gets Stuck on the Loading Screen. What Can I Do?](#)

Can I Control "Insert Pedal Name Here" w/ the Unity6?

Yes, no matter what pedal you have, we can control it!

If your pedal, synth, keyboard, software, etc has a 5-pin, ¼" TRS, or Bluetooth MIDI connection we can control it!

If you have an analog pedal and you need to control the on/off state of the pedal, just place it in one of the Unity6's 6 loops and we can turn it on and off!

Will the Unity6 Allow Me to Have Snapshots for my Pedalboard?

Short answer.... YES!

The Unity6 can send 32 MIDI messages per preset, each switch (and the BPM knob) is a preset. Not only do you have 5 presets per bank (127 banks total), each preset can group "mini presets" together meaning you can have up to 7 different presets per switch. This gives you a total of 35 presets per bank offering plenty of control and flexibility for Snapshotting your whole rig!

Are the 6 Loops Mono or Stereo?

All 6 loops are mono and run in series. For connecting and controlling stereo pedals we suggest placing these pedals after the Unity6's Output and controlling them with MIDI commands. Almost all stereo pedals are MIDI capable and can use MIDI commands to bypass (turn on/off), adjust parameters, and recall presets.

Can I Add a 2-Button Aux Switch to the Unity6?

No this is not a feature that the UniPorts support, however we do offer the U6 Trio to expand the number of switches available to the Unity6. You can read more about the U6 Trio [here](#).

Is There a Set List Feature in the Unity6?

Set lists can be used to organize your banks in a specific order for easy bank navigation for a given group of songs/banks. There are two different ways to streamline bank navigation within the Unity6.

1) The Unity6 has a Copy | Paste | Swap feature that can be used to quickly and easily move banks around in any specific order. See [here](#) for more information on this feature.

2) The Unity6 has two different Message Types to quickly and easily jump from bank to bank. The "Jump to Bank" message type can be assigned to any Press Action on any switch (including the BPM dial). When engaged, the Unity6 will immediately jump to the desired bank. This message can be assigned to each bank in your setlist and allows you to quickly jump to any bank and in any order you choose. The Unity6 also has a "Last Used Bank" message type, when engaged it will immediately jump back to the last used bank.

Is There a Factory Reset for the Unity6?

Yes, If you ever run into an issue where the Unity6 gets stuck on the loading screen, or simply want to wipe the pedal back to factory settings. You can hold down switches 1 & 3 upon applying power to the pedal and then follow the onscreen prompts.

My Unity6 Gets Stuck on the Loading Screen. What Can I Do?

If you ever run into an issue where the Unity6 gets stuck on the loading screen, or simply want to wipe the pedal back to factory settings. You can hold down switches 1 & 3 upon applying power to the pedal and then follow the onscreen prompts.